

**Table des matières**

*Démarrer conteneur LXC en mode debug / console* ..... 3  
*Serial console* ..... 3



## Démarrer conteneur LXC en mode debug / console

```
start -lDEBUG -o /tmp/112.log -F -n 112
```

### Serial console

```
# open /etc/pve/qemu-server/101.conf and add the following parameter at the end of file
serial0: socket
```

```
qm set 101 -serial0 socket
```

### On guest

```
dmesg | grep ttyS
[ 0.457814] 00:0a: ttyS0 at I/O 0x3f8 (irq = 4) is a 16550A
```

```
# in /etc/default/grub change the GRUB_CMDLINE_LINUX parameter to
GRUB_CMDLINE_LINUX="quiet console=tty0 console=ttyS0"
```

```
update-grub
```

```
/etc/init/ttyS0.conf
```

```
# ttyS0 - getty
```

```
#
```

```
# This service maintains a getty on ttyS0 from the point the system is
# started until it is shut down again.
```

```
start on stopped rc or RUNLEVEL=[2345]
stop on runlevel [!2345]
```

```
respawn
```

```
exec /sbin/getty -L 9600 ttyS0 vt102
```

### connect to console

```
qm terminal <VMID>
```

From:  
<https://unix.ndlp.info/> - Where there is a shell, there is a way

Permanent link:  
<https://unix.ndlp.info/doku.php/informatique:nix:linux:proxmox?rev=1637568858>

Last update: 2021/11/22 08:14