

Table des matières

<i>zvol timeout</i>	3
<i>Démarrer conteneur LXC en mode debug / console</i>	3
<i>Serial console</i>	3

zvol timeout

```
systemctl restart systemd-udev; udevadm trigger; udevadm settle
```

Démarrer conteneur LXC en mode debug / console

```
lxc-start -lDEBUG -o /tmp/112.log -F -n 112
```

Serial console

```
# open /etc/pve/qemu-server/101.conf and add the following parameter at the end of file  
serial0: socket
```

```
qm set 101 -serial0 socket
```

On guest

```
dmesg | grep ttyS  
[ 0.457814] 00:0a: ttyS0 at I/O 0x3f8 (irq = 4) is a 16550A
```

```
# in /etc/default/grub change the GRUB_CMDLINE_LINUX parameter to  
GRUB_CMDLINE_LINUX="console=tty0 console=ttyS0,115200n8"
```

```
update-grub
```

```
systemctl enable --now serial-getty@ttyS0.service
```

```
=== connect to console ===
```

```
<code>
```

```
qm terminal <VMid>
```

From:
<https://unix.ndlp.info/> - **Where there is a shell, there is a way**

Permanent link:
<https://unix.ndlp.info/doku.php/informatique:nix:linux:proxmox?rev=1768390167>

Last update: 2026/01/14 11:29