

# Table des matières

<b>SWITCH SAN</b> .....	1
<b>MDS-SERIES (CISCO) COMMANDS</b> .....	1
MDS-SERIES Switch Commands .....	1
MDS-SERIES Zoning Commands .....	1
<b>B-SERIES (BROCADE) COMMANDS</b> .....	1
B-SERIES Switch Commands .....	1
B-SERIES Zoning Commands .....	2
<b>M-SERIES (McDATA) COMMANDS</b> .....	2
M-SERIES Switch Commands .....	2
M-SERIES Zoning Commands .....	2
<b>Veritas VM HOST COMMANDS</b> .....	3
<b>Veritas VM Device Commands</b> .....	3
<b>Veritas VM Filesystem commands</b> .....	3
<b>VMware ESX HOST COMMANDS</b> .....	3
<b>VMware ESX Device Commands</b> .....	3
<b>VMware ESX Filesystem Commands</b> .....	4
<b>AIX/IBM HOST COMMANDS</b> .....	4
<b>AIX Software Installation</b> .....	4
<b>AIX Device Commands</b> .....	4
<b>AIX iSCSI Commands</b> .....	4
<b>HP/UX HOST COMMANDS</b> .....	4
<b>HP/UX Software Installation</b> .....	5
<b>HP/UX Device Commands</b> .....	5
<b>HP SAN Commands</b> .....	5
<b>HP iSCSI Commands</b> .....	5
<b>PROCEDURES</b> .....	5
<b>zone hp server to symm</b> .....	5
<b>Linux HOST COMMANDS</b> .....	6
<b>Linux Device Commands</b> .....	6
<b>Linux FC SAN Commands</b> .....	6
<b>Linux iSCSI Commands</b> .....	7
<b>SUN/SOLARIS HOST COMMANDS</b> .....	7
<b>SOLARIS Software Installation</b> .....	7
<b>Solaris Device Commands</b> .....	7
<b>Solaris iSCSI Commands</b> .....	8
<b>Solaris FC SAN Commands</b> .....	8
<b>SOLUTIONS ENABLER COMMANDS</b> .....	8
<b>Commands to see devices</b> .....	8
<b>Symdev Commands</b> .....	8
<b>Symcfg Commands</b> .....	9
<b>Symconfigure Commands</b> .....	9
<b>Symmaskdb Commands</b> .....	9
<b>Symmask Commands</b> .....	9
<b>Other SYMCLI Commands</b> .....	10
<b>NAVICLI COMMANDS</b> .....	10
<b>POWERPATH COMMANDS</b> .....	11
<b>INQ COMMANDS</b> .....	11



# SWITCH SAN

## MDS-SERIES (CISCO) COMMANDS

### MDS-SERIES Switch Commands

```
ip address 191.168.123.234 255.255.255.0
View =          show running-config
show environment  shows status of all installed hardware components
show flogi database shows database list of all FLOGI events
show fcns database shows database list of all N-ports logged in
show vsan membership  shows list of VSAN members
show interface brief  lists the interfaces and status
```

### MDS-SERIES Zoning Commands

```
config terminal          Enters configuration terminal
zone name TestZone1 vsan 4      creates a zone
member pwwn 10:01:10:01:10:ab:cd:ef  adds node to the zone above
no member pwwn <colon separated wwn>  deletes member from zone
zoneset name Zoneset1 vsan 4    creates a zoneset
member <zone name>              adds zone to the ZoneSet above
no zone name <zone name> vsan <vsan Id>  Deletes a zone
zoneset activate name Zoneset1 vsan 4
zone copy active-zoneset full-Zoneset1 vsan 4
copy running-config start-up config  copy from source to startup
configuration
vsan database                go into vsan configuration mode
vsan 4 interface fc3/21      move port 21 on module 3 to vsan 4
show zoneset                 shows all zonesets that are active
show zone vsan <#>           shows all zones active in vsan
show zoneset active          displays the active zoneset
show vsan                    shows the vsans on the switch
show zoneset active vsan <vsan Id>  Shows active zoneset
```

## B-SERIES (BROCADE) COMMANDS

### B-SERIES Switch Commands

```
switchDisable      offline
ipAddrSet          set the IP address of a Brocade switch
switchShow         display switch info
supportShow        full detailed switch info
```

```
portShow #      display port info
nsShow          Name server contents
nsAllShow      NS for full fabric
fabricShow     fabric information
ad --create    create a new Admin Domain.
ad -apply      enforce the new Admin Domain configuration.
```

## B-SERIES Zoning Commands

```
aliCreate "Alias", "20:00:00:e0:69:40:07:08"
zoneCreate "Zone1", "20:00:00:e0:69:40:07:08; 50:06:04:82:b8:90:c1:8d"
cfgCreate "Test_cfg", "Zone1; Zone2"
cfgSave      saves zoning information across reboots
cfgEnable "Test_cfg"
zoneShow or cfgShow  shows defined and effective zones and configurations
zoneAdd      adds a member to a zone
zoneRemove   removes a member from a zone
zoneDelete   deletes a zone
cfgAdd       adds a zone to a zone configuration
cfgRemove    removes a zone from a zone configuration
cfgDelete    deletes a zone from a zone configuration
cfgClear     clears all zoning information/ must disable the
effective configuration
```

## M-SERIES (McDATA) COMMANDS

### M-SERIES Switch Commands

```
View=          config ip show
Config> ip      (new IP and Subnet mask)
Show> switch
Show> switch
Show > system
Show> nameserver
Show> loginServer
Show> nameServer
Show.Fabric> nodes
Maint > system > setOnlineState
```

### M-SERIES Zoning Commands

```
Config.Zoning> addWwnMem: <zoneName> <wwn>
Config.Zoning> addZone      add a new zone to the working area
Config.Zoning> activateZoneset  activation of changes
Config.Zoning> showactive    shows actively connected running zoneset
Config.Zoning> clearZone     clear WWNs in a zone
```

```

Config.Zoning> deletezone      remove zone from the running config
Config.Zoning> showPending    show pending zones
Config.Zoning> renameZone:<oldzonename><newzonename>
Config.Zoning> deleteWwnMem    <zonename><wwn>
Config.Zoning> renameZoneSet   <zoneSetName>

```

## Veritas VM HOST COMMANDS

- <http://www.symantec.com/business/support/documentation.jsp?language=english&view=manuals&pid=15273>

## Veritas VM Device Commands

```

vxdisk list      List all disks under volume manager control and give there
status.
vxdiskadd clt2d3  add or bring a disk under volume manager control
vxdiskadmin      Interactive front end to the vxdisk program

```

## Veritas VM Filesystem commands

```

vxdisk init      Initialize Physical Volume
vx dg init mydg mydg-01=clt11d0      Create Disk Group
vxassist -g mydg make myvol <size>  Create Logical Volume
mkfs -F vxfs /dev/vx/rdisk/mydg/myvol create file system
vxvol -g mydg stopall                stop a volume
vx dg deport mydg                    deport disk group
vx dg import mydg                    import disk group
vxvol -g mydg startall               starting a imported volume

```

## VMware ESX HOST COMMANDS

- <http://www.b2v.co.uk/b2vguide2vmware.htm>
- <http://b2v.co.uk/b2vguide2vmware3.htm>

## VMware ESX Device Commands

```

esxcfg-rescan <vmkernel adpater> scan for new disks
esxcfg-swiscsi -e                enable iSCSI initiator
more /proc/scsi/lpfc/X            wwn of HBA
esxcfg-vswitch

```

## VMware ESX Filesystem Commands

vmkfstools

~

## AIX/IBM HOST COMMANDS

- <http://publib.boulder.ibm.com/infocenter/pseries/v5r3/index.jsp?topic>

### AIX Software Installation

```
/usr/lpp                Software Directory
lslpp -L all            List installed software
lslpp -f fileset       List all files
instfix -i             List installed patches
cp *.lpp /usr/sys/inst.images  copy lpp software to the install directory
smit installp         Install a software package
rmdev                 Remove a device
```

### AIX Device Commands

```
lscfg                 lists all configured components
smit or smitty        system management utility
lscfg -v l <interface> lists all attributes (WWN's) for a device
emc_cfgmgr           configures symmetrix devices
mkbcv                makes BCV visible to AIX to avoid locking during boot
(1) chdev -l fcsX -a init_link=pt2pt -P      "To change INIT Link flags
parameter"
(2) chdev -l fscsiX -a fc_err_recov=fast_fail -P  "Fabric Event Error
RECOVERY Policy"
(3) cfgmgr -v        configures devices and optionally installs device
software
```

### AIX iSCSI Commands

smit iscsi

## HP/UX HOST COMMANDS

- <http://www.docs.hp.com/en/B2355-90681/index.html>

## HP/UX Software Installation

```

sysdef          analyzes current running system
swlist -l bundle  displays version and type of HP-UX
swlist -l patch   List installed patches
swreg -l depot /full/path/to/your/depot_file  Register a depot package for
install
swinstall       Install the Software depot

```

## HP/UX Device Commands

```

insf -e         install special device files
ioscan -fnC disk  scans system hardware
sam            System administration tool
dd if=/dev/rdisk/c34t15d0 of=/dev/zero count=1  makes HP register with a
Clariion thru LUNZ device
navicli -h <SP IP>  register                registers host with Clariion and tests
agent install
lsdev -C disk     list device drivers in the system
mknod           makes a directory, special, or ordinary file
/stand/system    system configuration file

```

## HP SAN Commands

```

fcmsutil /dev/fcd0  List HBA wwn
tdutil /dev/td0     List HBA wwn

```

## HP iSCSI Commands

- <http://docs.hp.com/en/T1452-90011/T1452-90011.pdf>

# PROCEDURES

## zone hp server to symm

```

symmask list hba -v          to list your servers paths to the symm
symmask -wwn -dir -p add dev  (use wwn, dir, p values from above
command) run command for each hba to FA zone
symmask -wwn -dir -p set heterogeneous on HP_UX  use wwn from the
(symmask list hba -v )
symmask refresh

```

```
ioscan -fnC disk
insf -e
symcfg dis
sympd list
```

- To get HPUX to register with Clariion if using NaviAgent

```
Install NaviAgent
Edit agent.config file
ioscan -fnC disk
insf -e
/sbin/init.d/agent stop
rm /etc/log/HostIdFile.txt
/sbin/init.d/agent start
dd if=/dev/rdisk/c34t15d0 of=/dev/zero count=1          makes HP register with a
Clariion thru LUNZ device
navicli -h <SP IP> register                            registers host with Clariion and
tests agent install

# rmsf path ( The paths are showing NO_HW or not sensing).
# ioscan -fnc disk (check)
# insf -e
# symcfg discover
# powermt display ( check for any dead path)
# powermt check (checks and corrects dead path).
# powermt config
# powermt save
```

## Linux HOST COMMANDS

- <http://www.redhat.com/docs/manuals/enterprise/RHEL-5-manual/en-US/>

## Linux Device Commands

```
modprobe -l *lpfc*          List Emulex modules
modprobe -r                 discover new disk
/sys/class/scsi_host/host1/issue_lip    discover new disk
/sys/class/scsi_host/host1/scan        discover new disk
/usr/sbin/lpfc lun_scan all
```

## Linux FC SAN Commands

```
more /proc/scsi/lpfc/X          wwn on RHEL3
more /sys/class/scsi_host/hostX/port_name    wwn on RHEL4
more /sys/class/fc_host/hostX/port_name     wwn on RHEL5
```



(X is the instance number of the HBA)

## Linux iSCSI Commands

```
yum install iscsi-initiator-utils          install iSCSI soft initiator
rpm -q srvadmin-deng iscsi-initiator-utils  install iSCSI soft initiator
rpm -ql iscsi-initiator-utils              confiure iSCSI soft initiator
iscsiadm -m discovery -t -p 192.168.1.100  discover iSCSI target
iscsiadm --mode node --targetname iqn
```

## SUN/SOLARIS HOST COMMANDS

- [http://developers.sun.com/openstorage/articles/opensolaris\\_storage\\_server.html](http://developers.sun.com/openstorage/articles/opensolaris_storage_server.html)

## SOLARIS Software Installation

```
ptree -a      Shows all running processes in a tree format
showrev -p   Displays currently installed Solaris patches
prtconf      prints system configurations
pkginfo      lists installed software packages
pkgadd       install software packages
pkgrm       removes installed software packages
```

## Solaris Device Commands

```
cfgadm -a      list all
cfgadm -c c4   configure c4   configure StorEdge Leadville driver.(Search for new
devices)
devfsadm -vC   searches for devices and also cleans up old
update_drv -f sd -d -I  searches for devices
devinfo       print device specific information about disk devices
drvconfig     generates special device files
reboot -- -r   reboots system to discover configuration changes, and
rebuild special files
/etc/system   system files
/kernel/drv/sd.conf lists of available target ids and luns
/kernel/drv/lpfc.conf  used for persistent binding on Emulex (qla22xx.conf
for Qlogic)
/var/adm/messages  system messages
```

## Solaris iSCSI Commands

```
iscsiadm add static-config
iqn.1999-08.com.array:sn.01234567,192.168.1.3:3260    map target
iscsiadm add discovery-address 192.168.1.13:3260
iscsiadm modify discovery --isns enable
iscsiadm list target -vS Target: iqn.1986-03.com
devfsadm -Cv -i iscsi
```

## Solaris FC SAN Commands

```
fcinfo hba-port                Lists information and WWNs
fcinfo remote-port -p 10000000c937694f -ls Lists the remote-port
information
```

# SOLUTIONS ENABLER COMMANDS

## Commands to see devices

```
syminq          ~ list all devides seen by host OS
syminq -cids    ~ list Clariion devices
syminq hba -fibre ~ list HBA
syminq -pdevfile ~List the location of devices
sympd list      ~ lists the Symmetrix devices that the host OS can see
sympd list -vcm ~ lists all the physical device name in the device
masking database
symdev list pd ~ lists the Symmetrix devices that the host OS
can see
symdisk
```

## Symdev Commands

```
symdev list      ~ list all devices on symm
symdev -sa -p list ~ list devices maped to that one FA
symdev list -bcv or -rdf1 ~ list all bcv or rdf1 volumes
symdev list -noport ~ list devices not mapped to any FE
ports
symdev list -clariion
symdev show 0123 -v ~ vebose listing of one device
symdev list -RANGE 0001:0123 -v ~ vebose listing of a rage of
devices
```

```
symdev list pd ~ list devices this host can see
```

## Symcfg Commands

```
symcfg discover ~ discover the storage environment
symcfg list ~ list local and remote symmetrixes
symcfg list -clariion ~ list clariions
symcfg list -v ~ lists whether the Symmetrix director has device
masking turned on
symcfg list -FA all list ~ lists all fibre directors in a Symmetrix
system
symcfg list -dir all -address -sid 6196 ~ identify the address
information for devices
symcfg list -dir all -address -available ~ sid 6196 ~
returns the next available LUN address
symcfg list -lockn all ~ list of visible Symm exclusive locks
symcfg -sid 098712341357 -lockn 15 release ~ release a lock on a
Symmetrix array.
```

## Symconfigure Commands

```
symconfigure -sid <sid> -f <filename> preview ~ checks file to make
sure it is ok to exe
symconfigure -sid <sid> -f <filename> commit ~ makes the changes
from file
symconfigure -sid <sid> -f <filename> prepare
```

## Symmashdb Commands

```
symmaskdb list devs ~ lists all devices accessible to an HBA on a
specified Symmetrix system
symmaskdb remove ~ removes the meta member devices
symmaskdb restore ~ restores a database from a specified file
symmaskdb backup ~ backs up a database to a specified file
symmaskdb init ~ deletes and creates a new VCMDB
symmaskdb list assignment ~lists deives already assigned
symmaskdb list no_assignment ~lists deives not yet assigned
```

## Symmask Commands

```
symmask add devs ~ adds a device to the list of devices that a WWN
can access in the database
symmask remove devs ~ removes a device from the list of devices
```

```

that a WWN can access in the database
symmask delete ~ deletes all access rights for a WWN in the
database
symmask replace ~ allows one HBA to replace another
symmask refresh ~ refresh vcmdb to all FA ports
symmask login ~ lists for each Fibre director which hosts and HBA's
are logged in to a Symmetrix system
symmask list HBA's ~ lists the WWN of the Fibre HBAs on this host
symmask -sid 381 -wwn 50060B000024F9F6 -dir 16C -p 1 set heterogeneous on
HP_UX
symmask -sid SymmID set lunoffset on offset base \ -awwn awwn -dir # -p #
~ offset high lun numbers

```

## Other SYMCLI Commands

```

symsan ~list ports and LUN WWNs seen from a specific Symmetrix
director and port
symdgm ~ creates/deletes/renames device groups
symld ~ adds & removes devices to a device group
symbcv ~ associates/disassociate BCV with device groups
symmir ~ performs (split/establish/restore) BCV mirror commands
against device groups
symclone ~ performs
(split/establish/restore/activate/terminate/recreate)
symsnap ~ performs (restore/activate/terminate/recreate)
symrdf ~ performs
(split/establish/restore/failover/update/failback/suspend/resume) against
RDF device groups
symcg ~ Performs operations on a Symmetrix RDF composite group
symrslv ~ Displays logical-to-physical mapping information about a
logical object that is stored on a disk.
symstat ~ Displays statistics information about a Symmetrix, any or
all directors, a device group, a disk, or a device.
symioctl ~ sends I/O control commands to application

```

## NAVICLI COMMANDS

```

navicli -h <host> getall --> Lots of useful and not so useful information
navicli -h <SP IP> getsp ~ verify connectivity
navicli -h <SP IP> register ~registers host with Clariion and tests
agent install
navicli -h <SP IP> storagegroup ~ list all info about existing
groups
navicli -h <SP IP> getrg -lunlist ~ list all existing raid groups
and LUNS
navicli -h <SP IP> getdisk ~ shows numbers of disks in storage array

```

```

navicli -h <SP IP> getrg <rg id>           ~ shows the number of raid groups
navicli -h <SP IP> getlun <lun id>         ~ lists all the disks
navicli -h <SP IP> storagegroup -list      ~ displays storage groups
navicli -h <SP IP> getcache                ~ shows the cache
navicli -h <SP IP> storagegroup -create -gname <name> ~ creates a
new storage group
navicli -h <SP IP> storagegroup -addhlu -gname <name> -hlu <#> -alu <#>
~ assigns LUNs to storage group
navicli -h <SP IP> storagegroup -connecthost -host <hname> -gname <gname>
~ assigns host to storage group

```

## POWERPATH COMMANDS

```

powermt ~ manage powerpath environment
powercf ~ configure powerpath devices
emcprep ~ manage powerpath license registration
emcpupgrade ~ convert powerpath configuration files

```

## INQ COMMANDS

```

inq -h ~ list options and syntax
inq -hba ~ list hba wwn
inq -btl ~ display Bus Target and Lun
inq -show_vol ~ display Symmetrix Volume Number.
inq -winvol ~ show Windows filesystems
inq -dev ## -page0 ~ Raw unformatted data on a single device
inq -clariion ~ display CLARiiON device information

```

From:  
<https://unix.ndlp.info/> - **Where there is a shell, there is a way**

Permanent link:  
[https://unix.ndlp.info/doku.php/informatique:nix:san:cmd\\_utiles](https://unix.ndlp.info/doku.php/informatique:nix:san:cmd_utiles)

Last update: **2017/03/27 14:21**

